


DETAIL LEGEND:

- ① FX LUMINAIRE "HS" FIXTURE PER PLAN
- ② DIRECT BURY UF/UL, COPPER, LOW VOLTAGE CABLE WITH UL 486D (IEC/EN 60998) RATED WATERPROOF CONNECTION. LEAVE 12" MINIMUM WIRE LOOP COILED IN CONSTRUCTION SLEEVE FOR FUTURE SERVICE.
- ③ WOODEN WALL
- ④ CUT A 7.5" X 1.75" REC HOLE THRU THE WOOD WALL TO MOUNT "HS" FIXTURE. MOUNT SLEEVE IN PLACE USING 1" #6 GALVANIZED DECK SCREWS.
- ⑤ IF WALL IS STUCCOED OR COATED, USE THE "CONSTRUCTION COVER" TO KEEP CAVITY CLEAN AND CLEAR OF DEBRIS.

NOTES

- A. INSTALL TO A UL 1838 (IEC/EN 61437) LISTED TRANSFORMER
- B. FIXTURE REQUIRES 10-15V AC/DC
- C. FIXTURE IS DESIGNED FOR DOWN LIGHTING ONLY. DO NOT USE IN UP LIGHT POSITION.
- D. FOR COPPER OR BRASS FIXTURES, AVOID PREMATURE PATINA BY HANDLING WITH GLOVES
- E. FOR LUXOR CONTROL, ASSIGN FIXTURE OR LUXOR CUBE® TO GROUP NUMBER PRIOR TO INSTALLATION



LED WALL LIGHT (HS) WOOD WALL MOUNT

FXLuminaire. W.HS.03

NOT TO SCALE
REV: 2020-07-17